

Ref:

DYANA-CH-3000K


Item No: 10924

orlight[®]
FROM SOURCE TO SITE

DYANA is an elegant wall light incorporating a 3W LED light source adding beautiful lighting to your scheme. It also rated to IP44 and is therefore suitable for bathrooms, creating a stylish alternative to the usual bathroom lighting. CREE 1512 chipset to enable superior performance with a CRI>80 light quality assurance. Colour consistency is adhered to with a 2-Step MacAdams Ellipse binning strategy. Please note: A remote mains dimmable driver is included with the fixture.



DIMENSIONS



OPTICAL PERFORMANCE

Wattage	3W
Lumen Output	270LM
Efficacy	90LM/W
CCT	3000K
CRI	CRI > 82
Binning	2 STEP MACADAMS
Chipset	CREE 1512
Chip Life	L70 > 60,500HRS

ELECTRICAL

Constant Current or Voltage	CONSTANT CURRENT
Voltage	240V
Driver Configuration	REMOTE
Control	MAINS DIMMABLE


CONSTRUCTION

Installation	WALL MOUNTED
Construction	ALUMINIUM & GLASS
Length	50 MM
Width / Depth	90 MM
Height	300 MM
Finish	CHROME
IP Rating	IP44

DYANA-CH-3000K


Item No: 10924

LIGHT DISTRIBUTION



ADDITIONAL DIMENSIONS

Remote Mains Dimmable Driver Included



FIXING DETAILS

