



Dimensions



Instructions


Step 1 – Prepare the Fixture

Carefully rotate and remove the decorative shade/body from the mounting plate to access the fixing points.




Step 2 – Mark and Drill Ceiling Holes

Hold the mounting plate against the ceiling and mark the three fixing points. Drill three holes at the marked positions using an appropriate drill bit for your ceiling material.



Step 3 – Insert Ceiling Plugs


Push the supplied wall plugs into the drilled holes until flush with the ceiling surface.



Step 4 – Connect the Wiring


Match the fixture wires to the mains supply wires and connect them according to the wiring diagram:

L – Live (Brown)
N – Neutral (Blue)
⬇ – Earth (Green/Yellow)




Step 5 – Fix the Mounting Plate

Lift the fixture body into position. Secure the mounting plate to the ceiling using the three screws, tightening each until the plate sits firmly against the surface.



Step 6 – Attach the Fixture Body


Align the shade/body with the mounting plate and rotate it clockwise to lock it into place. Ensure it sits securely and cannot loosen by hand.



Instructions Continue

Step 7 – Final Check

Ensure the fixture is level, wiring is enclosed, and the ceiling plate is flush. Switch on the power to test the light.



This product must be installed by a skilled or instructed person in accordance with the current edition of the IET Wiring Regulations BS 7671 "Requirements for Electrical Installations" and the Buildings Regulations, as may be applicable subject to the location and country of the installation.

Should this product be modified, misused or not installed as per the instructions given, the product warranty shall be rendered void.

All information contained within these installation instructions manual is provided in good faith. Orlight shall not be held responsible for any losses incurred as a result of the Customer's failure to follow the instructions manual thoroughly and in its entirety or failing to inspect the product for missing parts and/or any defects prior to installation.

For full Terms and Conditions, please visit our website at: <https://www.orlight.com/en/terms-and-conditions.html>

Hole Cut Out:

Orlight does not recommend cutting of holes prior to receipt of product in hand. Please refer to reverse or Orlight's technical support/website for recommended hole cut out.

Wiring:

Disconnect the mains supply before installation. Ensure that the unit is installed and maintained by a certified professional and that installation conforms to any local building control standard applicable.

Accessories:

Please ensure that any accessory used in conjunction with these products is approved by Orlight. Failure to do so will void any product guarantee. Orlight will not be held responsible for any loss incurred be it direct or consequential.

NOTE – Light fittings in general can become hot whilst in operation. It is advisable that they do not come into contact with any flammable materials such as fabrics, furniture, soft furnishings or touched during/after operation.